



312 Sunnyfield Drive, Suite 200  
Glenshaw, PA 15116-1936

877-77PROXI (toll free)  
412-213-2477 (tel)  
412-492-9386 (fax)  
[www.proxicast.com](http://www.proxicast.com)

---

**Total Cable Assembly Signal Loss in dB Including Connectors**  
(lower is better)

<b>Frequency MHz</b>	<b>10 ft CFD 195</b>	<b>15 ft CFD 240</b>	<b>25 ft CFD 240</b>	<b>36 ft CFD 400</b>	<b>50 ft CFD 400</b>	<b>75 ft CFD 400</b>
700	1.1	1.1	1.9	1.4	1.9	2.9
900	1.3	1.3	2.1	1.6	2.2	3.3
1700	1.8	1.8	3.0	2.3	3.1	4.6
1900	1.9	1.9	3.2	2.4	3.3	4.9
2400	2.1	2.2	3.6	2.7	3.7	5.6
2700	2.3	2.3	3.8	2.9	4.0	5.9
5000	3.2	3.2	5.3	4.1	5.6	8.3
5800	3.4	3.5	5.7	4.4	6.1	9.1