

# MK270 keyboard is not working or loses connection frequently

## Keyboard isn't working

When your MK270 keyboard isn't working, the problem is likely a lost a connection. The connection between the keyboard and the Unifying receiver can be lost for several reasons, such as:

- Low battery levels
- Moving the receiver from one USB port to another
- Moving the receiver to another computer
- Plugging the receiver into a USB hub or other unsupported device such as a KVM switch (**NOTE:** Your receiver must be plugged directly into your computer)
- Using your wireless keyboard on metal surfaces
- Radio frequency (RF) interference from other sources, such as:
  - Wireless speakers
  - Computer power supplies
  - Monitors
  - Cell phones
  - Garage door openers

## Before connecting your keyboard:

1. Fix or rule out the potential problems listed above.
2. Insert new batteries. For instructions on changing your keyboard batteries, see answer [27099](#).
3. Make sure the keyboard is turned on. For instructions on turning on your keyboard, see answer [27104](#).
4. Plug the receiver securely into a working USB port on your computer.
5. Turn your computer on.

## Reconnecting your keyboard

1. Download the correct version of Logitech SetPoint Mouse and Keyboard Software from the MK270 [Downloads Page](#).
2. Launch the Logitech Unifying Software:

Windows: Start > Programs > Logitech > Unifying > Logitech Unifying Software

3. Click **Next** at the bottom of the Welcome screen.
4. Follow the on-screen instructions to turn your keyboard off and then back on.



5. When your keyboard is detected, you'll see this window:



If you can type in the testing box, select **Yes** and then click **Next**. Otherwise, repeat from step #4.

6. Click **Finish** to exit the Logitech Unifying Software. Your keyboard should now be connected.

---

### Keyboard frequently stops working

If your keyboard frequently stops working and you keep having to reconnect it with the Unifying receiver, try these suggestions:

- Keep other electrical devices at least 8 inches (20 cm) away from the USB receiver
- Move the keyboard closer to the USB receiver
- Move the receiver to a different USB port on your computer