



SECURIFI

Almond

Dual Purpose Router with a Touch Screen



Wireless N Router
upto 300 Mbps
(2x2 MIMO)

Range Extender
compatible with any
existing router

Intuitive.



**Configure Settings
without a PC/Mac.**

Just connect your cable
and follow the on-screen
instructions.

Secure.



**Benefit from pre-
configured security.**

Prevent intruders from
accessing your wireless
data.

Fast.



**Up to 300Mbps using
802.11n MIMO tech.**

Connect up to 50 users at
a time. Compatible with
older 802.11bg devices.

Elegant.



**All your info is just
a finger tap away.**

The user interface is
a quantum leap over
existing routers.

Tech Specs.

Hardware	Processor: Ralink RT3052F 384MHz Memory: 64 MB RAM, 16 MB Flash Display: Color LCD/TFT 2.8", 320x240
Networking	WAN: 1 x Ethernet 10/100Mbit LAN: 2 x Ethernet 10/100Mbit WLAN: IEEE 802.11b, IEEE 802.11n, IEEE 802.11g
Wireless Connection	2 x SSID Encryption: 64/128/256-Bit WEP, WPA, WPA2 300Mbps (MIMO) in 802.11n mode Bandwidth: 2.4GHz (DSSS, OFDM, MIMO) Channels: 1~11 CH(FCC), 1~13 CH (ETSI), 1~14 CH (Japan) Max. range: up to 50m inside buildings, up to 100m outside
Misc.	Pin code for LCD access Clock and weather information Screen saver Firmware update via internet

Protocols and Features	TCP/IP, UDP, ICMP, PPPoE, PPTP, L2TP, NAT/PAT, DHCP, DDNS, WPS SPI Firewall, DMZ, Port Forwarding Advanced content filtering methods (URL blocking, keywords blocking) Filtering of IP and MAC addresses MAC address cloning (for WAN) WAN connection in router mode: DHCP, DSL, manual IP Operation modes: router, access point, repeater (WiFi range extender)
Management and Configuration	Via touch LCD screen Via web browser Hidden advanced features (via WWW) Settings available via LCD display (without using PC): Selection of operation mode (router, AP, repeater), activation and configuration of Guest access (Guest SSID), internet connection settings, WiFi security settings, AP mode settings, IP and MAC addresses info, WPS control, passwords check and updates, firmware update, system log view (last several entries), data transfer counter, URL/Keywords filtering, user filtering (IP/MAC), DMZ settings, weather, clock.
Languages (for WWW and LCD)	English, German, French, Spain, Portuguese, Russian, Chinese, Japanese, Swedish, Dutch, Polish, Turkish
Build and casing	Black, made of metal and plastic, passive cooling, vertical operation. LCD and power led at the front, LAN sockets, reset button and power connector at the right side. Stylus for LCD hidden at the bottom side. Two internal WiFi antennas
Power supply and usage conditions	External AC/DC adapter (110-240V AC), 5V, 1A, EU and UK plug Temperatures: 10°C - 50°C Humidity: 10%~90%RH (without condensation)
Size and weight	117 x 125 x 50 mm [HxWxD] approx. 370g (without AC/DC adapter)
In the box	Router, stylus, LAN cable, AC/DC adapter, Quick Start Guide, Warranty card



Securifi Ltd.
+886-2-2726-0100
sales@securifi.com
www.securifi.com