


Quick Installation Guide

AC1900 Wireless Dual Band Gigabit Router

Archer C9

Connect the Hardware

If your internet connection is through an Ethernet cable directly from the wall instead of through a DSL / Cable / Satellite modem, connect the Ethernet cable to the router's Internet port, and then follow Step 1, 5 and 6 to complete the hardware connection.



Configure the Cloud Router

Method ONE: Via TP-Link Tether App

1. Download the Tether app.




2. Connect your smartphone to the router.

The default wireless network names (SSIDs) and password are printed on the label at the back of the router.




3. Connect the router to the internet.



- A** Launch the Tether app. Select Archer C9 from the local device list.
- B** Create a login password and then enter the password again to log in.
- C** Follow the steps to connect to the internet.

4. Register the TP-Link Cloud service.



With TP-Link ID, you can conveniently manage your home network from your smartphone or tablet via the Tether app, no matter where you find yourself.


Enjoy the internet !

Method TWO: Via Web Browser

1. Connect your device to the router (wired or wireless).

• Wired


Turn off the Wi-Fi on your computer and connect the devices as shown below.



• Wireless

a Find the SSID and wireless password printed on the label of the router.


b Click the network icon of your computer or go to Wi-Fi settings of your smart device, and then select the SSID to join the network.




2. Connect the router to the internet.

A Launch a web browser, and enter <http://tplinkwifi.net> or <http://192.168.0.1> in the address bar. Create a login password and then click Let's Get Started.

Note: If the login window does not appear, please refer to Q1 of Need Help? in this guide.




B Follow the step-by-step instructions to set up the internet connection and register the TP-Link Cloud service.



Enjoy the internet !

USB Applications

With the dual USB ports, it's easy to share printers, files and media with multiple devices.




- Local Storage Sharing**
Share files from the USB drive with devices on your home network
- Printer Sharing**
Share a printer with multiple computers connected to the router
- Remote Access**
Access the USB drive when you are away from home
- Media Server**
Play media from the USB drive on your computer and smart devices



To learn more about the USB applications, visit <http://www.tp-link.com/app/usb>, or simply scan the QR code.

TP-Link Cloud Service

TP-Link Cloud service provides a better way to manage your cloud devices. For example:




- Remote Management**
Easily manage your home network when you are out and about via the Tether app on your smartphone or tablet.
- Timely Upgrade Notifications**
Keep informed of the latest firmware updates, ensuring your router stays at its best.
- One for All**
Manage multiple TP-Link Cloud devices, all from a single TP-Link ID.

You can set up and enjoy cloud functions via the Tether app or through the web management page at <http://tplinkwifi.net>.

To learn more about TP-Link Cloud service and other useful features supported by the router (including Guest Network, Parental Controls, Access Control and more), please refer to the User Manual at www.tp-link.com.

Need Help?

- Q1. What can I do if the login page does not appear?**
 - If the computer is set to a static or fixed IP address, change settings to obtain an IP address automatically.
 - Verify that <http://tplinkwifi.net> is correctly entered in the web browser. Alternatively, enter <http://192.168.0.1> or <http://192.168.1.1> in the web browser and press Enter.
 - Use another web browser and try again.
 - Reboot your router and try again.
 - Disable and enable the network adapter being used.
- Q2. What can I do if I cannot access the internet?**
 - Check if the internet is working normally by connecting a computer directly to the modem using an Ethernet cable. If it is not, contact your Internet Service Provider.
 - Log in to the web management page of the router, and go to the **Basic > Network Map** page to check whether the Internet IP address is valid or not. If it is, please run the Quick Setup again; otherwise, recheck the hardware connection.
 - Reboot your router and try again.
 - For cable modem users, log in to the web management page of the router. Go to **Advanced > Network > Internet > MAC Clone**, click **Use Current Computer MAC Address** and click **Save**. Then reboot both the modem and the router.
- Q3. How do I restore the router to its factory default settings?**
 - With the router powered on, press and hold the **Reset/WPS** button on the back until the Power LED blinks.
 - Log in to the web management page of the router. Go to **Advanced > System Tools > Backup & Restore**, and click **Factory Restore**. The router will restore and reboot automatically.
- Q4. What can I do if I forgot my web management password?**
 - If you are using a TP-Link ID to log in, click **Forgot password** on the login page and then follow the instructions to reset it.
 - Alternatively, press and hold the **Reset/WPS** button on the back until the Power LED blinks to reset the router, and then visit <http://tplinkwifi.net> to create a new login password.
- Q5. What can I do if I forgot my wireless network password?**
 - If you have not changed the default wireless password, it can be found on the label at the back of the router.
 - Connect a computer directly to the router using an Ethernet cable. Log in to the router's web management page at <http://tplinkwifi.net>, and go to **Basic > Wireless** to retrieve or reset your wireless password.
- Q6. How can I mount the router to the wall?**
 - The two mounting brackets coming with the router can help you mount the router to the wall if needed.



For technical support and other information, please visit <http://www.tp-link.com/support>