

User Guide

- ▶ Please remember that if you have any issues or questions at any time, you can contact Walabot support: **support@walabot.com**
- ▶ Walabot DIY 2 connects to your phone via its own Wi-Fi network and interfaces with your phone via a free app. Walabot sends and receives radio frequency signals to detect objects inside walls. The app and phone process the data to create visual representations of the objects.
- ▶ The app is available from the Google Play Store and the Apple App Store. Please search for “*Walabot DIY App*”.
- ▶ We regularly update the Walabot DIY app with new features, advanced capabilities, and improved user experience. These updates can be downloaded from our app page (Walabot DIY) on the Google Play Store or the App Store by selecting “*Upgrade*”.
- ▶ Walabot DIY 2 detects objects up to a depth of 4 inches /10 centimeters in drywall. It detects wood and metal studs, stud centers, metal pipes, PVC/plastic pipes, wires and conduits. It can also detect movement, such as rodents running through the wall, termite nests, and beehives.
- ▶ Walabot DIY 2 can be used on walls containing insulation as long as the insulation does not contain metal and is not metal-backed.
- ▶ Walabot DIY 2 uses radio frequency (RF) technology that is approved by the FCC and CE and can be used without limitation. The radio waves emitted by the device do not pose any health threat.