

**PBC-302/Train-Well  
Bark Control Collar™  
Over Mold Version**

**\*\*Train-Well model is like the BC-103OM and sold through Drs. Foster & Smith (FS-103)**



1. Set up collar: Install battery. Align arrow on battery with triangle on unit. Using a coin or straight edge screwdriver, turn battery to right to align arrow on battery with lock on unit.
2. Test Collar: Slide Sensor Probe across a rough surface for at least 10 inches. The Bark Control Collar should beep. If collar does not beep, try a rougher surface.
3. Observe Dog: Do not leave the dog alone the first few times he receives the Static Correction.
4. Remove Battery: Using a coin or straight edge screwdriver, turn the battery to the left to align arrow on battery with triangle on unit. The battery can now be removed.
5. Discharge Unit: After removing the battery, the unit retains some stored storage and may activate 2 or 3 more times. To discharge, slide the Sensor Probe across a hard surface several times until it stops beeping.

*Note: Avoid touching the Contact Points and Sensor Probe unless the unit is completely discharged.*

**Important:**

- **The Bark Control collar should not be worn for more than 8 hours out of every 24 hour period.**
- **Do not use the Bark Control Collar with any additional collars, tags, leashes or other items that may cause vibration and trigger a false correction. A harness is a good alternative for attaching a leash and/or tags while using the Bark Control Collar.**
- **Before playing with your dog, remove the Bark Control Collar. The activity may cause your dog to bark, which could lead to him associating the play with the Static Correction.**
- **For use on dogs weighing 8 pounds on up**

**PetSafe® Bark Control Collar™ Features**

Accessory kit: (RFA-225 through Distributor Channel) Includes 2 medium contact points, 2 washers and 1 battery

Battery: Uses (RFA-67)\* Battery Life = 3-6month\*\* Must order battery/cover combo Available through RSC or Radio Shack (23-366) or Batteries Plus (RFA-67) Battery 2 pack (RFA-67D-11) available through RSC

\* The unique battery is designed for ease of battery replacement and increase water protection

\*\* Battery life is dependent on the number of corrections your dog receives.

*Due to greater use during your dog's training, your first battery may not last as long as replacement batteries*

Collar: BC-103OM (RFA-354) Battery replaceable and waterproof  
Collar measures 2" wide x 1.25" tall x 1" thick, weighs 3.5 oz with strap & battery  
Red nylon web quick release strap, ¾", 3 holes, fits necks up to 27 ½" (RFA-264)  
Shipping weight: 2 pounds

Collar Features: Indicator Light = Low battery indicator  
Contact Points = Delivers the Static Correction (Medium length only)  
Sensor Probe = Detects the vibrations of the dog's bark (Not adjustable)  
Washers = Located under the Contact Points

Collar Lights: No light = Normal unit operation or dead battery  
Blinking red = Low battery indicator (1 flash every 4 seconds)

Flashing red = Static correction delivered (4 flashes)

Contact Points: Comes with Medium Points installed  
Comes with No Correction Caps that cover the points to prevent the dog from receiving the correction (No longer packaged with system)

Collar Maintenance: Check collar fit frequently.  
Check Contact Points for tightness weekly  
**Note: Do not adjust the factory preset Sensor Probe.**  
Clean Contact Points with alcohol weekly  
**Note: Remove the battery and discharge the collar before touching probes**  
Check dog's neck for irritation and wash neck weekly

OM version: Over Mold, same unit case but has a special over mold that gives additional coverage that reduces the risk of false readings.

QuickFit™ Strap: Designed so you can quickly attach and remove Bark Control Collar from dog while maintaining the desired fit.

Resistor: 1M Ohm ¼-watt resistor, reduces static correction by 15% – 20%  
Radio Shack part # 271-1356

Safety Shutoff: The unit will automatically shut off for 3 minutes if dog barks 15 times or more within a 50-second period.

Sensor Probe: Detects the vibrations of the dog's bark (Not adjustable)

Stimulation: 6 levels of stimulation. Self adjusts based on the dog's barking habits. Starts at level 1, and then increases each time the dog barks within 30 seconds of the previous bark. If the dog remains quiet for 30 seconds, the collar will reset back to level 1. Activation is caused by vibration of vocal cords.

Tone: Along with each Static Correction, there will be an audible tone

Warranty: Limited Lifetime Warranty

### **PetSafe® Bark Control Collar™ Troubleshooting Tips**

Check battery for proper installation  
Test for working unit

Unit does not activate: Lift up the battery contact located inside the unit and retest  
Replace battery

Unit does not beep: Test for a working unit. If still does not beep during this test, try the same test on a rougher surface.  
Ensure battery is properly installed  
Replace battery

Dog not responding: Ensure proper collar fit. Place Bark Control Collar high on dog's neck close to the ears. Sensor Probe centered on the front of the dog's neck. Allow 1 finger to fit between the end of Contact Point and the dog's neck.  
Trim dog's hair where the Contact Points touch his neck.  
Replace battery

Dog in bark-correction cycle: On rare occasions, a dog may get into a bark-correction-bark-correction cycle. Reassure the dog with calm, soothing tones. As the dog relaxes, he will understand that if he becomes quiet, he will not receive any more Static Corrections. The small minority of dogs that have this reaction should only have it the first time they wear the Bark Control Collar.

### **PetSafe® Bark Control Collar™ FAQ's**

Will my dog stop barking completely? The Bark Control Collar effectively stops barking when it worn. It should only be worn during periods of unwanted barking.

Will another dog's bark set off the Bark Control Collar? No

Is the Bark Control Collar safe and humane? Yes. The collar is designed to get the dog's attention, not to punish him. However the initial Static Correction may startle the dog.

Will the Bark Control Collar work for my dog? The collar is safe and effective for all breeds and sizes of dogs, though it may be too large for dogs under 8 pounds to wear comfortably.

Will this work with longhaired dogs? Yes. It may be necessary to trim the hair around the Contact Points to make sure that contact is consistent.