

XP4400EH

DUAL FUEL PORTABLE GENERATOR
4,400 STARTING WATTS • 3,500 RUNNING WATTS






XP4400EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS



X2
120V 20A
GFCI Outlet



X1
120/240V
30A Twist
Lock



DOUBLE THE
120V AMPERAGE

SPECS

Watts (Gasoline)	4,400 (peak) • 3,500 (running)
Watts (Propane)	4,180 (peak) • 3,325 (running)
Engine	OHV 210cc
Amperage	29.17A / 14.58A
Voltage	120V / 240VAC & 12VDC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	11.46 hrs
Runtime (Propane) at 50% Load	9.81 hrs