



Auto Fish Feeder Program Setting Guide

Model number: CY-009



- How Do We Start?

1. Switch on/off: Press the power button for 3 seconds.



2. Calibrate real-time clock
(To make sure the fish feeder drop food on time)



3. Finish real-time clock





- Choose the Applicable Mode

- **Mode I: Custom Feeding Mode**

For fish that need to be fed multiple times a day. Supports up to four automatic feedings per day, and the number of feedings can be customized.

- **Mode II: Simple Interval Feeding Mode**

For fish that only need to be fed once at regular intervals. Support every 8H/12H/24H/48H auto feeding once.

- **Mode III: Immediate Manual Feeding**

Feed the fish manually at any time

Petbönk - Attention

When the real-time clock is set, the program will automatically enter the Custom Feeding Mode settings.

If you want to choose the custom feeding mode, keep going with the next page setting guidance.

If you do not want to choose this mode, instead of pressing the up/down button to select the time, press "MANUAL" to quit, and the interface returns to display the real time, and then refer to the interval feeding mode settings.





- How to Set Mode I

- Mode I: Custom Feeding Mode

Feeding Time Setting

Hour/Minute number flashes
Press “▲” or “▼” to adjust



Feeding Circle Number Setting

Press “▲” or “▼” to adjust
the number (1 2 3)
of feeding circles



Set Feed Time : Press "SET" button, the hour number and the first box flash. Press "+" or "-" to adjust the hours, press "SET" again to adjust the minute number.

Set the Number of Turns : Continue to press "SET" button with the first box flashes, then click '+' or '-' to adjust the number of feeding laps you want (1 for 1 cycle, 2 for 2 cycles, 3 for 3 cycles).



- How to Set Mode I

- Mode I: Custom Feeding Mode



If you want to do multiple time feeds in a day (up to 4 times each day), repeat the previous steps.

If not, keep the rest box blank, and press "MANUAL" to save the current setting and exit.



- How to Set Mode I

- **Mode I: Custom Feeding Mode**

Note: In this mode, you can set up to four different time points for automatic feeding, each time point can set a different feeding amount (increase the feeding amount by increasing the number of turns of the feeder, up to 3 turns per meal). After the setting is successful, the feeder will automatically drop the amount you set at the corresponding time everyday.





- How to Set Mode II

- **Mode II: Simple Interval Feeding Mode**

Press "+" and "-" buttons simultaneously to enter 8H/12H/24H/48H programmed interval feeding mode.



Press "+" or "-" button to select one interval time. The corresponding box will flash when the time is selected. This programmed feeding mode feeds once at the default time. And the countdown will start again after each feeding.

Note: If you want to feed fish food at an exact time, set this interval feeding mode at that time.



- How to Set Mode II

- Mode II: Simple Interval Feeding Mode



If there is no activity for more than 5 seconds, the setting is automatically saved and the display will lock. If you need to adjust it again, press "+" or "-" button for 3 seconds to unlock.

Press "+" and "-" buttons simultaneously again to exit smart interval feeding mode, and back to customised feeding mode.



- How to Reset the Program

Long press “” for
5 seconds to delete all settings





- Mode III: Immediate Manual Feeding



Note: Manual feeding does not affect the preset program

Attention!

After fixing the position of the feed slider, please use manually feeding test whether the amount of food dropped by the rotation of the feeder is reasonable before feeding to avoid excessive feeding by the fish!

- Contact Us

- You can watch the operation guide video on the Petbank Facebook page:

<https://www.facebook.com/watch/?v=672094934426888>

- If you encounter any problem during use, please feel free to contact us, we'll reply promptly.



 <http://www.petbank-tec.com/>

 customer-support@petbank-co.com

 INS: @petbankfans

 FB: @Petbank