

Automatic Wire Stripper User Manual



Read Carefully Before Use
Keep for Future Reference

Safety Information

Warning!

- Keep your work area clean and well lit. Cluttered or dark areas invite accidents.
- Keep children and bystanders away while using this product.
- **DO NOT** allow individuals unfamiliar with this device to operate it.
- **DO NOT** use this device with an incompatible power source.
- **NEVER** use this device without its provided safety guards.
- **DO NOT** place fingers or appendages near or in the openings.
- **ALWAYS** use proper safety equipment such as gloves and safety goggles while using this product.
- **DO NOT** wear loose clothing or jewelry during use. Keep your hair, clothing, and gloves away from moving parts.
- **DO NOT** operate this device in overly humid conditions.

Specifications

Input Voltage	220V/50Hz
Rated Power	180W
Compatible wire gauges	1.5–25 mm (7/0–15 AWG)
Dimensions	24×32×32 cm (9.4×12.5×12.5 in.)
Gross Weight	11.7 kg (26 lb.)

Product Diagram



Operation

1. Press the start button and adjust the depth of the cutting blade using its adjustment knob.
2. Feed smaller insulated wires through the narrower bottom hole. Feed wires with a diameter between 5 and 14.5 millimeters through the wider top hole. For larger wires, turn off the machine and remove the two bolts holding the safety guard in place. Remove the guard itself, turn the machine back on, and carefully feed your wire directly into the machine. (Remember to turn the machine back off before using the bolts to reattach the security guard.)
3. Peel the insulation off of the wire. If the cut is not deep enough to remove the insulation, further adjust the depth of the cutting blade.

Maintenance

- Periodically clean the machine of dust and debris with a soft cloth wetted in a mild detergent solution. Do not use harsh chemicals.
- Regularly inspect the bolts, screws, and moving parts of the machine. Ensure that they are properly tightened before use.
- Brush away any debris created by the cutting of the insulation before it accumulates under the blade.

Contact Us

Thank you for choosing our products! If you have any questions or comments, contact us at **help@cs-supportpro.com** and we'll resolve your issue ASAP!

For a .pdf copy of the latest version of these instructions, use the appropriate app on your smartphone to scan the QR code to the right.



