

ScanSnap

ScanSnap iX100

*World's Lightest, Fastest, Wi-Fi Equipped,
Built-In Battery Scanner*



shaping tomorrow with you


FUJITSU

ScanSnap iX100, productivity unleashed.

Scan a colour document in just **5.2 seconds***

*Single-side color A4 document scanned at 300 dpi.



Lightweight

Only 400g (14.1 oz)

Power on the Move

Rechargeable Lithium Battery

Wi-Fi and USB Connectivity

Scan wirelessly to your PC, Mac and mobile devices

Wireless scanning anywhere, anytime

The ScanSnap iX100 can automatically detect your Wi-Fi network at home, in the office or on the go. With *Direct Connect* mode you can scan wirelessly beyond your network.

At home At the office On the road



Built-in GI microprocessor

A dual-core CPU-mounted "GI" processor performs the intelligent image enhancement responsible for great looking images with dramatically faster results and more sophisticated connectivity:



- Image processing: Automatic corrections and image output
- Supports Wi-Fi: 2.4GHz, WPS (Wi-Fi Protected Setup), Wireless LAN IEEE802.11b/g/n

Intelligent automated features

Like all ScanSnap scanners, ScanSnap iX100 features a powerful set of automated image processing functions that include auto colour detection, crop & deskew, and blank page removal.



Easily synchronize documents to the cloud

ScanSnap iX100 provides users a convenient way to scan directly to your existing Evernote, Dropbox, Google Docs, SugarSync and Salesforce accounts.*

*Wi-Fi connection required. Service fees may apply.

Scan there! ScanSnap Folder

Scan to virtually any application or web service that open, insert or attach a PDF or JPEG file from your Windows® computer.



Organize business cards

Scan, store, edit business card information with the bundled CardMinder software for Mac and PC, and even export data into other applications such like Address Book, Excel®, and Salesforce.

Fast and flexible Quick Menu

The Quick Menu for PC and Mac automatically pops up after scanning to provide you a variety of ways to be immediately productive with your scans. It can be customized to display just your favorites, present a recommendation, and even display custom profiles.



Generate Microsoft® Word®, Excel® and PowerPoint® files

ABBYY FineReader for ScanSnap lets you scan and convert paper documents into Word®, Excel® and PowerPoint® files.

Only Microsoft® Word and Excel® are available for Mac OS. Generated images and text may vary from the original.

New features for quick digitization



Dual scan
Scan two small sized documents, such as business cards or receipts at the same time. Simply insert documents continuously to reduce your scanning time.




Automatically stitch together a two-page spread
Even charts and diagrams larger than A4 can be scanned. Just fold it in half, scan both sides and the ScanSnap iX100 will automatically stitch it back together.


Two selectable paper paths

Straight path
Most suitable for scanning post cards, business cards, plastic cards, and thick stock paper.

*This applies to standard ISO 7810 ID-1 card types.



U-turn path
Most suitable for scanning common office paperwork, especially in a tight or cluttered environment.



Continuous Document Feeding (CDF)

The Continuous Document Feeding function allows you to insert pages one after another by detecting when a sheet enters and exits.



Set your document face up into the iX100 and push the Scan button.



The iX100 proceeds to scan the front side.



The page exits from the top of the scanner when paper path is set to U-turn.



Re-insert the page without pressing the Scan button to scan the other side.



After completing the scan, press the Scan button to save file.

■ General Specifications

| | |
|---------------------------------|---|
| Description | ScanSnap iX100 / PA03688-B001 |
| Scanner type | CDF (Continuous Document Feeding), Simplex sheetfed two-way paper path (Straight path, U-turn path) |
| Scanning modes | Color, grayscale, monochrome, automatic (color / grayscale / monochrome detection) |
| Image sensor | CIS (Contact Image Sensor) x 1 |
| Light source | 3 Colour LED (Red / Green / Blue) |
| Optical resolution | 600 dpi |
| Scanning speed *1 (A4 portrait) | Auto mode (default) *2 |
| | Normal mode (150 dpi) |
| | Better mode (200 dpi) |
| | Best mode (300 dpi) |
| | Excellent mode (600 dpi) |
| Document size *3 | Normal mode |
| | Normal mode with Carrier Sheet |
| | Long paper scanning *4 |
| Paper weight (Thickness) | <ul style="list-style-type: none"> 52.3 to 209.3 g/m², or 14 to 56 lb (Straight path) 52.3 to 80 g/m², or 14 to 20 lb (U-turn path) Card: <ul style="list-style-type: none"> Portrait or Landscape (Straight path) Non-embossed: 0.76 mm or less Embossed: 0.76 + 0.48 mm (ISO7810 Conforming) |
| Paper setting | Front-side up |
| Continuous scanning | 260 sheets (A4, colour, simplex, 300 dpi, battery operated) *5 |
| Interface *6 | USB 2.0 (USB 1.1 compatible) |
| Power source | Li-ion Battery (3.7 V / 720 mAh) |
| Power requirement | 5 V / 0.5 A (x 1port) |
| Power consumption *7 | During operation: 4.7 W or less During sleep mode: 2.2 W or less During Auto Standby (OFF) mode: Less than 0.5 W |
| Operation environment | Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80% (Non-condensing) |
| Dimensions (W x D x H) *8 | 273 x 47.5 x 36 mm (10.74 x 1.87 x 1.42 in.) |
| Device weight | 400 g (0.88 lb) |
| Environmental compliance | ENERGY STAR® compliant/RoHS/EPEAT® Silver |
| Multifeed detection | None |
| Driver | ScanSnap specific driver <ul style="list-style-type: none"> Windows®: Does not support TWAIN / ISIS® Mac OS: Does not support TWAIN |

*1 Scanning speeds may vary due to the system environment used. Scanning speed measured from "start feeding document" to "finish output document" after pre-pick and pressing scan button (not including warm-up time). Warm-up time is less than 2 seconds (or less than 3 seconds from chute cover closed). *2 Documents measuring approximately 148 mm in length or less are scanned in "Best mode", while other documents are scanned in "Better mode". *3 Automatically stitch a two-page spread when scanning a folded A3, B4 or double letter size document one side at a time. The image is automatically stitched only if texts or diagrams cover across the two-page spread. *4 The iX100 is capable of scanning documents that exceed A4 size in length. This function is available for all modes except for "Excellent mode". *5 The number of sheets that can be scanned when connected to a computer via Wi-Fi with a fully charged battery. The number of sheets may vary due to the system environment used, usage method and repeated charging. *6 Computer with USB 3.0 will work as USB 2.0 guaranteed only with USB cable provided with product. *7 When operating with battery. *8 When chute is closed.

■ Software

| | Windows® | Mac OS |
|--------------|--|---|
| Driver *1 | ScanSnap Manager V6.3 (TWAIN / ISIS™ not supported) | ScanSnap Manager V6.3 (TWAIN not supported) |
| Applications | ScanSnap Organizer V5.2 | ScanSnap Organizer V1.1 |
| | CardMinder™ V5.2 | CardMinder™ V5.2 |
| | ABBYY FineReader for ScanSnap™ 5.0 Scan to Microsoft® SharePoint® | ABBYY FineReader for ScanSnap™ 5.0 - |

*1 TWAIN or ISIS™ applications cannot be used directly.

■ Included items

● Getting started ● Set-up DVD-ROM ● USB cable 50cm (0.5m)

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

©2014 Fujitsu Computer Products of America, Inc. All rights reserved. Fujitsu and the Fujitsu logo are registered trademarks of Fujitsu Limited. *ABBYY and FineReader are trademarks of ABBYY Software, Ltd. which may be registered in some jurisdictions. ABBYY™ FineReader™ Engine ©2011 ABBYY. OCR by ABBYY. *Evernote is a registered trademark or trademark of Evernote Corporation. *Google and Google Docs are registered trademarks or trademarks of Google Inc. *Intel, Pentium, and Intel Core are trademarks or registered trademarks of Intel Corporation in the United States and other countries. *ISIS® is a registered trademark of EMC Corporation in the United States. *Mac, Mac OS, Mac logo and iPhoto are trademarks of Apple Inc. *Microsoft, Windows, Windows Vista, Excel, PowerPoint and SharePoint are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. *Word is the products of Microsoft Corporation in the United States. *PowerPC is a registered trademark or trademark of International Business Machines Corporation in the United States, other countries, or both. *Salesforce and Salesforce CRM are registered trademarks or trademarks of salesforce.com, inc. in the United States and other countries. *ScanSnap, ScanSnap logo, ScanSnap Manager, ScanSnap Organizer and CardMinder are registered trademarks or trademarks of PFU LIMITED in Japan. *Other company names and product names are the trademarks or registered trademarks of the respective companies. Specifications are subject to change without notice.

■ ScanSnap iX100 System Requirements

● Windows®

| Compatible operating systems | | Windows® 8 / 8.1 (32-bit / 64-bit) | Windows® 7 (32-bit / 64-bit) *1 | Windows Vista® (32-bit / 64-bit) *2 |
|------------------------------|------------------------------------|--|---------------------------------|-------------------------------------|
| Driver / Applications *3 | ScanSnap Manager V6.3 | Supported | Supported | Supported |
| | ScanSnap Organizer V5.2 | Supported | Supported | Supported |
| | CardMinder™ V5.2 | Supported | Supported | Supported |
| | ABBYY FineReader for ScanSnap™ 5.0 | Supported | Supported | Supported |
| | Scan to Microsoft SharePoint 3.4 | Supported | Supported | Supported |
| Hardware requirements *4 | CPU *5 | Intel® Core™ i5 2.5 GHz or higher | | |
| | Memory capacity *5 | 4 GB or more | | |
| | Display | 1,024 x 768 pixels or higher | 800 x 600 pixels or higher | |
| | Disk capacity *6 | 2,690 MB or more of free hard disk space | | |
| | DVD-ROM drive | Required for installation | | |
| | USB port *5 *7 | USB 2.0 / USB 1.1 | | |

*1 Service Pack 1 or later required. *2 Service Pack 2 or later required. *3 Operating systems listed in this table are the only ones supported. Please refer to the ScanSnap Web site for latest support information. *4 The ScanSnap device may not work if the connected computer does not meet this requirement. *5 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *6 Microsoft .NET Framework 3.5 SP1 will be installed (requires 500 MB of disk space) together with either ScanSnap Manager or ScanSnap Organizer for systems that do not have .NET Framework 3.5 SP1 installed. *7 When the ScanSnap is connected to a USB 3.0 port, the port operates as a USB 2.0 port. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

● Mac OS

| Compatible operating systems | | OS X v10.9 *1 | OS X v10.8 *2 | Mac OS X v10.7 *3 |
|------------------------------|------------------------------------|--|---------------|-------------------|
| Driver / Applications *4 | ScanSnap Manager V6.3 | Supported | Supported | Supported |
| | ScanSnap Organizer V1.1 | Supported | Supported | Supported |
| | CardMinder™ V5.2 | Supported | Supported | Supported |
| | ABBYY FineReader for ScanSnap™ 5.0 | Supported | Supported | Supported |
| Hardware requirements *5 | CPU *6 | Intel® Core™ i5 2.5 GHz or higher | | |
| | Memory capacity *6 | 4 GB or more | | |
| | Display | 1,024 x 768 pixels or higher | | |
| | Disk capacity | 1,930 MB or more of free hard disk space | | |
| | DVD-ROM drive | Required for installation | | |
| USB port *6 *7 | USB 2.0 / USB 1.1 | | | |

*1 OS X v10.9.1 or later recommended. *2 OS X v10.8.5 recommended. *3 Mac OS X v10.7.5 recommended. *4 Operating systems listed in this table are the only ones supported. Please refer to the ScanSnap Web site for latest support information. *5 The ScanSnap device may not work if the connected computer does not meet this requirement. *6 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *7 When the ScanSnap is connected to a USB 3.0 port, the port operates as a USB 2.0 port. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

■ Options

| Description | Part number | Remarks |
|-----------------------------|--------------|--|
| AC adapter | PA03010-6581 | Intended for ScanSnap iX100 |
| ScanSnap iX100 Case *1 | PA03688-0001 | Intended for ScanSnap iX100 |
| ScanSnap iX100 Soft Case *1 | PA03688-0011 | |
| ScanSnap Carrier Sheets *2 | PA03360-0013 | 5 Carrier Sheets Intended for ScanSnap iX500, iX100, S1500, S1500M, S1100i, S1100 |

*1 This product has been especially designed for storing and carrying ScanSnap iX100. Please note that this product is not guaranteed to withstand damage by excessive shock or external pressure. *2 Although ScanSnap Carrier Sheets have a listed lifespan of 500 scans, the lifespan may vary with usage. ScanSnap Carrier sheets are intended to scan paper documents with weights of 127 g/m² or less. They also support the scanning of folded documents that are as large as 216 x 297 mm.

■ Consumables

| Description | Part number | Remarks |
|---------------|--------------|---|
| Cleaner F1 | PA03950-0352 | 100 ml bottle Used to clean rollers |
| Cleaning Wipe | PA03950-0419 | 1 pack (24 sheets) Used to clean rollers |



This product is a green product and Fujitsu promotes recycling for the scanner. PFU LIMITED, a Fujitsu company, has determined that this product meets the ENERGY STAR® guidelines for energy efficiency. ENERGY STAR® is a registered trademark of the United States.

Scan Here



For more information, please visit <http://www.fujitsu-scansnap.com>

| Safety Precautions | Be sure to carefully read all safety precautions prior to using this product and use this device as instructed. | Do not place this device in wet, moist, steamy, dusty or oily areas. Using this product under such conditions may result in electrical shock, fire or damage to this product. | | | | |
|--|---|---|--|---|--|--|
| Singapore (Regional Headquarter) Fujitsu Asia Pte Ltd (Singapore) Tel: +65 6512 7555 Fax: +65 6512 7502 | Indonesia PT Fujitsu Indonesia Tel: +62-21 570 9330 Fax: +62-21 573 5477 | India Fujitsu India Pvt. Limited Tel: +91 124 470 5100 Fax: +91 124 470 5198, 460 5199 | Malaysia (Malaysia) Sdn Bhd Fujitsu (Malaysia) Sdn Bhd Tel: +60-3 8318 3700 Fax: +60-3 83188700 | Philippines Fujitsu Philippines, Inc. Tel: +63-2 812 4001 Fax: +63-2 8177576 | Thailand Fujitsu Systems Business (Thailand) Ltd. Tel: +66-0 2302 1500 Fax: +66-0 2302 1555 | Vietnam Fujitsu Vietnam Limited Tel: +84 4 220 3113 Fax: +84 4 22203114 |